
TAVAKOL ELECTRONIC
توکل الکترونیک
مرجع تخصصی تأمین قطعات الکترونیکی اورجینال
این دیتاشیت توسط توکل الکترونیک تهیه و ارائه شده است.
جهت مشاهده قیمت، موجودی و ثبت سفارش این قطعه به وب‌سایت توکل الکترونیک مراجعه فرمایید.
مشاهده قیمت و خرید
برای خرید و مشاهده سایر محصولات کلیک کنید

Power Darlington Modules

T-39-31

900 VOLT IGBTs (FOR RESONANT APPLICATIONS)


Device Type	V_{CES} Volts (min)	Ic Amps (min)	Rth (j-c) °C/Watts (max)	V_{GE}(th) Volts (max)	V_{CE}(sat) Volts (max)	tfi µs (max)	tf2 µs (max)	Package
IMB50-090A	900	50	0.83	6	3.6	0.5	1.0	T03P
MBT001	900	60	0.41	6	4.0	0.5	1.0	T03PL



IGBT GATE DRIVERS

IGBT	600 V IGBT drive		1200 V IGBT drive	
	Up to 150A	Up to 400A	Up to 75A	Up to 300A
Standard type	EXB850	EXB851	EXB850	EXB851
High-speed type	EXB840	EXB841	EXB840	EXB841

Notes: 1. Standard type: Signal delay in drive circuit; Up to 4 µs
2. High-speed type: Signal delay in drive circuit; Up to 1 µs



INTELLIGENT POWER MODULES (IPM)

GENERAL DESCRIPTION

Fuji has recently introduced Smart Power, Intelligent Power Modules (IPM) for motor controllers. The modules integrate: power electronics, base drive, protection and isolation into one package.

IPMs are designed for 230VAC, 3-phase operation with current ranges from 10A to 150A. Packages contain either six or seven switching devices. Compatible soft start converters and dynamic break modules are also available.

BENEFITS

- Reduce design time.
- Isolated signal inputs.
- No base drive design required.
- Logic level controllable.


FEATURES


- Overcurrent protection.
- Overtemperature protection.
- Diagnostic output.
- Shunt regulator.

SELECTION GUIDE

Device Type	VCC Volts (Max)	IC Amps	PC Watts (Per Transistor)
6D10A-050EJR	450	10	40
6D15A-050EJR	450	15	60
6D20A-050EJR	450	20	80
7D30A-050EHR	450	30	150
7D50A-050EHR	450	50	200
7D75A-050EHR	450	75	240
7D100A-050EHR	450	100	350
7D150A-050EHR	450	150	400

Converter and Dynamic Brake Modules Designed to be used with the IPM.






SELECTION GUIDE

Device Type	V_{RRM} Volts	Io (AV) Amps
4R3TI20Y-080	800	20
4R3TI30Y-080	800	30
4R3TI60Y-080	800	60
6R1TI30Y-080	800	30

Inverter Modules



SELECTION GUIDE

Device Type	V_{CBO} Volts	Ic Amps	Pc Watts
2R6D15A-050AJV	600	15	60
2R6D20A-050AJV	600	20	80

FUJI Semiconductors • Imported and Distributed by:
Collmer Semiconductor, Inc.
14368 PROTON • DALLAS, TEXAS 75244 • 800-527-0251
FAX 214/233-0481

www.datasheet.world
http://store.iiic.cc/